

Technical data sheet Multiple light beam safety device receiver

Part no.: 66043700 MLD312-XR4



 The Sensor People
 Leuze electronic GmbH + Co.

 In der Braike 1, 73277 Owen

Leuze electronic GmbH + Co. KG info@leuze.com • www.leuze.com In der Braike 1, 73277 Owen Phone: +49,7021,573-0 • Fax: +49

Phone: +49 7021 573-0 • Fax: +49 7021 573-199 eng

We reserve the right to make technical changes eng • 2021-02-02

Technical data

Leuze

| Series | MLD 300 |
|---|---|
| evice type | Receiver |
| unctions | |
| unctions | Activation input for test and series connection |
| | Automatic restart |
| haracteristic parameters | |
| | 2, IEC/EN 61496 |
| ype IL | 1, IEC 61508 |
| ILCL | 1, IEC/EN 62061 |
| erformance Level (PL) | c, EN ISO 13849-1 |
| | 204 years, EN ISO 13849-1 |
| FH _D | 1.2E-08 per hour |
| lission time T _M | 20 years, EN ISO 13849-1 |
| Category | 3, EN ISO 13849 |
| | ., |
| ptical data | |
| umber of beams | 4 Piece(s) |
| eam spacing | 300 mm |
| lectrical data | |
| rotective circuit | Overvoltage protection |
| | Short circuit protected |
| | · |
| Performance data | |
| Supply voltage U _B | 24 V, DC, -20 20 % |
| Current consumption, max. | 150 mA, Without external load |
| Fuse | External with max. 3 A |
| | |
| Inputs | 1 Piece(s) |
| Number of digital switching inputs | 1 F IECE(S) |
| | |
| Switching inputs | |
| Switching inputs Type | Digital switching input |
| Туре | Digital switching input 18.2 V |
| Type Switching voltage high, min. | |
| Type Switching voltage high, min. Switching voltage low, max. | 18.2 V |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. | 18.2 V 2.5 V |
| Type Switching voltage high, min. Switching voltage low, max. | 18.2 V 2.5 V 23 V |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type | 18.2 V 2.5 V 23 V DC |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type | 18.2 V 2.5 V 23 V DC |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. | 18.2 V 2.5 V 23 V DC |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 | 18.2 V 2.5 V 23 V DC 5 mA |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment | 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 2 |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment | 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 2 |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Outputs Number of safety-related switching | 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 2 |
| Type Switching voltage high, min. Switching voltage low, max. Switching voltage, typ. Voltage type Switching current, max. Digital switching input 1 Assignment Function Outputs | 18.2 V 2.5 V 23 V DC 5 mA Connection 1, pin 2 Test signal input |

| Safety-related switching out | outs |
|--|--------------------------------------|
| Туре | Safety-related switching output OSSD |
| Switching voltage high, min. | 18.2 V |
| Switching voltage low, max. | 2.5 V |
| Switching voltage, typ. | 23 V |
| Voltage type | DC |
| Current load, max. | 380 mA |
| Load inductivity | 2,200,000 µH |
| Load capacity | 0.3 µF |
| Residual current, max. | 0.2 mA |
| Residual current, typ. | 0.002 mA |
| Voltage drop | 1 V |
| C . | |
| Safety-related switching o | utput 1 |
| Assignment | Connection 1, pin 4 |
| Switching element | Transistor, PNP |
| | |
| Timing | |
| Response time | 25 ms |
| Restart delay time | 100 ms |
| Connection | |
| Number of connections | 1 Piece(s) |
| | |
| Connection 1 | |
| Function | Machine interface |
| Type of connection | Connector |
| Thread size | M12 |
| Material | Metal |
| No. of pins | 5 -pin |
| | |
| Cable properties | |
| Permissible conductor cross section, typ. | 0.25 mm² |
| Length of connection cable, max. | 100 m |
| Permissible cable resistance to | 200 Ω |
| load, max. | 200 12 |
| | |
| Nechanical data | |
| Dimension (W x H x L) | 52 mm x 1,000 mm x 64.7 mm |
| Housing material | Metal |
| Metal housing | Aluminum |
| Lens cover material | Plastic / PMMA |
| Material of end caps | Diecast zinc |
| Net weight | 2,200 g |
| Housing color | Yellow, RAL 1021 |
| Type of fastening | Groove mounting |
| | Swivel mount |
| Operation and display | |
| | LED |
| Type of display | |
| Number of LEDs | 1 Piece(s) |
| Environmental data | |
| | |
| Ambient temperature, operation | -30 55 °C |
| Ambient temperature, operation Ambient temperature, storage | -30 55 °C -40 75 °C |

 The Sensor People
 In der Braike 1, 73277 Owen
 Phone: +49 7021 573-0 • Fax: +49 7021 573-199
 eng • 2021-02-02

Leuze electronic GmbH + Co. KG info@leuze.com • www.leuze.com

Technical data

Leuze

Certifications


| Degree of protection | IP 67 |
|----------------------|----------------|
| Protection class | III |
| Certifications | c CSA US |
| | c TÜV NRTL US |
| | TÜV Süd |
| US patents | US 6,418,546 B |
| | US 7,741,595 B |
| | |


| Classification |
|----------------|
|----------------|

| Customs tariff number | 85365019 |
|-----------------------|----------|
| eCl@ss 5.1.4 | 27272703 |
| eCl@ss 8.0 | 27272703 |
| eCl@ss 9.0 | 27272703 |
| eCl@ss 10.0 | 27272703 |
| eCl@ss 11.0 | 27272703 |
| ETIM 5.0 | EC001832 |
| ETIM 6.0 | EC001832 |
| ETIM 7.0 | EC001832 |

Dimensioned drawings

All dimensions in millimeters





Electrical connection


Connection 1

| Function | Machine interface |
|--------------------|-------------------|
| Type of connection | Connector |
| Thread size | M12 |
| Туре | Male |
| Material | Metal |
| No. of pins | 5 -pin |
| Encoding | A-coded |

Electrical connection

Leuze

| Pin | Pin assignment | Conductor color | 2 |
|-----|----------------|-----------------|---|
| 1 | +24V | Brown | |
| 2 | Test in | White | |
| 3 | 0 V | Blue | 3 |
| 4 | OSSD | Black | |
| 5 | n.c. | Gray | 4 |



Operation and display

| LED | Display | Meaning |
|-----|-------------------------|--|
| 1 | Red, continuous light | OSSD off. |
| | Green, continuous light | OSSD on |
| | Red, flashing, 1 Hz | External error |
| | Red, flashing, 10 Hz | Internal error |
| | Green, flashing, 1 Hz | Weak signal, device not optimally aligned or soiled. |

Suitable transmitters

| _ | Part no. | Designation | Article | Description |
|---|----------|-------------|---|--|
| | 66001700 | MLD300-XT4 | Multiple light beam safety device transmitter | Operating range: 20 70 m Number of beams: 4 Piece(s) Beam spacing: 300 mm Connection: Connector, M12, Metal, 5 -pin |

Part number code

Part designation: MLDxyy-zab/t

| MLD | Multiple light beam safety device |
|-----|--|
| x | Series 3: MLD 300 5: MLD 500 |
| уу | Function classes 00: transmitter 10: automatic restart 12: external testing 20: EDM/RES 30: muting 35: timing controlled 4-sensor muting |
| Z | Device type T: transmitter R: receiver RT: transceiver xT: transmitter with high range xR: receiver for high range |
| а | Number of beams |

Part number code

| Leuze | |
|-------|--|
|-------|--|

| MLD | Multiple light beam safety device |
|-----|--|
| b | Option L: integrated laser alignment aid (for transmitter/receiver) M: integrated status indicator (MLD 320, MLD 520) or integrated status and muting indicator (MLD 330, MLD 335, MLD 510/A, MLD 530, MLD 535) E: connection socket for external muting indicator (AS-i models only) |
| /t | Safety-related switching outputs (OSSDs), connection technology -: transistor output, M12 plug A: integrated AS-i interface, M12 plug, (safety bus system) |
| | Note |
| 6 | ♥ A list with all available device types can be found on the Leuze website at www.leuze.com. |

Accessories

Connection technology - Connection cables

| | Part no. | Designation | Article | Description |
|--|----------|--------------------|------------------|---|
| | 50133859 | KD S-M12-5A-P1-020 | Connection cable | Connection 1: Connector, M12, Axial, Female, A-coded, 5 -pin Connection 2: Open end Shielded: Yes Cable length: 2,000 mm Sheathing material: PUR |
| | 50133860 | KD S-M12-5A-P1-050 | Connection cable | Connection 1: Connector, M12, Axial, Female, A-coded, 5 -pin Connection 2: Open end Shielded: Yes Cable length: 5,000 mm Sheathing material: PUR |
| | 50136146 | KD S-M12-5A-P1-250 | Connection cable | Connection 1: Connector, M12, Axial, Female, A-coded, 5 -pin Connection 2: Open end Shielded: Yes Cable length: 10,000 mm Sheathing material: PVC |

Services

| | Part no. | Designation | Article | Description |
|----|----------|-------------|--|---|
| () | S981050 | CS40-I-140 | Safety inspection "Safety light barriers" | Details: Checking of a safety light barrier application in accordance with current standards and guidelines. Inclusion of the device and machine data in a database, production of a test log per application. Conditions: It must be possible to stop the machine, support provided by customer's employees and access to the machine for Leuze employees must be ensured. Restrictions: Travel costs and accommodation expenses charged separately and according to expenditure. |
| ц. | S981046 | CS40-S-140 | Start-up support | Details: For safety devices including stopping time measurement and initial inspection. Conditions: Devices and connection cables are already mounted, price not including travel costs and, if applicable, accommodation expenses. Restrictions: Max. 2 h., no mechanical (mounting) and electrical (wiring) work performed, no changes (attachments, wiring, programming) to third-party components in the nearby environment. |

 Leuze electronic GmbH + Co. KG
 info@leuze.com • www.leuze.com

 The Sensor People
 In der Braike 1, 73277 Owen
 Phone: +49 7021 573-0 • Fax: +49

Phone: +49 7021 573-0 • Fax: +49 7021 573-199 eng • 2021-02-02

We reserve the right to make technical changes

Accessories





A list with all available accessories can be found on the Leuze website in the Download tab of the article detailed page.